

EVLALTAIR900-M1 Bill-of-materials

Reference	Part	Description	Note
R1		1.8kΩ	
R2		1.3Ω	1% tolerance
R3, R5		N.C.	
R4		8.2kΩ	
R6		8.2kΩ	1% tolerance
R7		27kΩ	1% tolerance
R8		5.1kΩ	1% tolerance
R9		0Ω	
C1	B41044A4108M	1000µF - 16V electrolytic	Epcos
C2	B41858C4477M	470µF - 16V electrolytic	Epcos
C3	B43851F9226M	22µF 400V electrolytic	Epcos
C4, C9		100nF ceramic – 25V	
C5	B41851A3477M	470µF - 10V electrolytic	Epcos
C6	B32922C3224M	220nF - X2	Epcos
C7		2.2nF Y-CAP	
C8		470nF ceramic - 25V	
C10		4.7nF ceramic - 25V	
C11		1nF ceramic - 25V	
C12		3.3µF - 35V electrolytic	
C13	ZLH series	100µF - 16V electrolytic	Rubycon
D1	STPS2150A	Power schottky diode	STMicroelectronics
D2	P6KE200A	Transil	STMicroelectronics
D3	STTH1L06A	Ultra-fast high voltage diode	STMicroelectronics
D4	STPS1L30A	Power schottky diode	STMicroelectronics
D5	BAT41	Small signal schottky	STMicroelectronics
PD1	DF06S	Input bridge rectifier	
L1	B82462G4472M	4.7µH power inductor	Epcos
L2	B82422H1105K	1mH SMT inductor	Epcos
IC1	ALTAIR04-900	Primary switching regulator	STMicroelectronics
Q1	LF33AB	3.3V LDO voltage regulator	STMicroelectronics
CM	B82721K2701	CM Choke	Epcos
	744612101		Wurth
TF1	SRW16EE-X129V005	Flyback transformer	TDK
	760-871-431		Wurth
NTC1	B57236S0160M	NTC Inrush current limiter	Epcos
RV1	B72214S0321K	320V Varistor	Epcos
F1		2A Fuse	
Notes: if not otherwise specified, all resistors are 5%, 1/4 W			