

STEVAL-CBL001V1 BOM

#	Quantity	Reference	Value / Generic Part Number	Package	Manufacturer	Manufacturer's ordering code / Orderable Part Number	Supplier	Supplier's ordering code
1	1	U6	L78M05CDT	D-PAK RSC/189-0977	ST			
2	1	U2	Female berg stick	16-pin			Farnell	1172524
3	1	U7	OTS-20(28)-1,27-04	SO-20 Socket	ENPLAS			
4	1	U3	ST72521	TQFP64 14X14	ST			
5	1	U4	LNBP15SP	POWER SO-10	ST			
6	1	U5	ST232ECDR	SO-16	ST			
7	1	R1	500R	CMS1206				
8	1	R2	12R	RB59				
9	2	R3,R6	10K	CMS1206				
10	1	R4	330K	CMS1206				
11	1	R5	100K	CMS1206				
12	1	R7	4K7	CMS1206				
13	3	C1, C13, C18	10µF	CMS1206 - NON POLARISE				
14	4	C2, C3, C4, C5	1µF	CMS1206 - POLARISE				
15	1	C11	10NF	CMS1206				
16	2	C7, C10	2.2µF-16V	CMS1206 - POLARISE				
17	2	C14, C15	33PF	CMS1206				
18	5	C6, C9, C12, C17, C16	100NF	CMS1206				
19	1	D2	Green	CMS1206 RSC/429-568	HP			
20	3	SW1, SW2, SW3	1K2	RSC/204-7865	EA0			
21	1	SW4	DTSML-3	BOUTON POUSSOIR				
22	1	CN1	MKDS1,5/2-5,08	RSC/193-0564	PHOENIX			
23	1	CN2	DB9	MALE COUDE				
24	1	CN3	SERIE F COUDE	RSC/196-2892	VITELEC			
25	1	JP1	HE10 2X5	MALE DROIT				
26	1	CR1	4 MHZ	HC49/U RSC/130-9229				
27	2	D1, D3	1N4001	RSC/261-148				