

Document reference: <b>STEVAL-ISA036V1</b>	PCB reference:	28/03/07
Company: <b>ST Microelectronics</b>		
Contact person: <b>Giuseppe Catalisano</b>	E-mail: <a href="mailto:giuseppe.catalisano@st.com">giuseppe.catalisano@st.com</a>	Phone: <b>95.7404096</b>

Index	Quantity	Reference	Value / Generic Part Number	Package	Manufacturer	Manufacturer's ordering code / Orderable Part Number	Supplier	Supplier's ordering code
Revised: Tuesday, June 27, 2006								
				DxL (mm)				
1	2	C1,C13	220µF / 25V					
2	3	C2,C3,C4	33µF / 450V	16x30mm(max)				
3	1	C5	.0022µF/250V					
4	1	C6	10nF / 50V	ceramico X7R				
5	2	C7,C8	1000µF / 25V					
6	1	C9	4.7nF / 50V	ceramico X7R				
7	1	C10	47µF / 25V	6mm				
8	1	C12	100pF / 50V	ceramico X7R				
9	4	D1,D2,D4,D5	STTH112U	SMB	ST			
10	2	D3,D11	STPS1H100A	SMA	ST			
11	2	D7,D12	LL4148					
12	1	D9	STPS3L60	DO201AD	ST			
13	1	D13	18V ZENER	DO41				
14	1	F1	TR5 FUSE 250mA	Radiale				
15	1	J1	Connector 3 pin	15x 9mm				
16	3	J2,J3,J4	Connector 2 pin	10x9mm				
17	1	L1	M600X					
18	1	<b>Q1</b>	<b>STC04IE170HP</b>	<b>TO247-4L</b>	<b>ST</b>			
19	1	<b>Q3</b>	<b>STP03D200</b>	<b>T)220</b>	<b>ST</b>			
20	1	Q4	2STR1160	SOT23-3L	ST			
21	6	R1,R2,R3,R7,R9,R10	150K	SMD 1206				
22	2	R4,R5	1.5M	SMD 1206				
23	1	R6	1	SMD 1206				
24	1	R8	47K	SMD 1206				

25	3	R11,R14,R28,R29	10K	SMD 1206				
26	1	R12	10	SMD 1206				
27	1	R13	22	SMD 1206				
28	6	R15,R17,R21,R30,R31,R32	56K	SMD 1206				
29	1	R18	22K	SMD 1206				
30	2	R22,R26	330	SMD 1206				
31	1	R23	4.7	1/2 W				
32	1	R24	2.2K	SMD 1206				
33	1	R25	220K	SMD 1206				
35	1	R33	1.5K	SMD 1206				
36	1	R34	680K	SMD 1206				
37	1	U1	L6565	SO8		ST		
38	1	U2	CSM 29-024			CRAMER		