

Date: 30-01-2007

Document reference: STEVAL-IAS001V1	PCB reference: CR.HSC0001.01
Company: STMicroelectronics	

Designator	Quantity	Reference	Value / Generic Part Number	Package	Manufacturer	Manufacturer's ordering code / Orderable Part Number	Supplier	Supplier's ordering code
U4	1	ST7FLite39F2M6 - MCU	ST7FLite39F2M6	SO-20	ST	ST7FLite39F2M6		
U3	1	EEPROM	M95080WMNP	SO-8	ST	M95080WMNP		
U2	1	Tamper Detect	STM1403ASNQ6F	QFN-16	ST	STM1403ASNQ6F		
U1	1	Voltage Regulator	KF33BDT-TR	DPAK-3	ST	KF33BDT-TR		
U5	1	RS-232 interface	ST3232	SO-16	ST	ST3232CDR		
D4	1	Diode	BAT54J	SOD-323	ST	BAT54JFILM		
J2	1	RS-232 connector		DB9/F			Farnell	105-6112
CON1	1	ICC Connector		Header 5x2/ IDC-10B			Farnell	1106782
D1	1	LED (green)		Through-hole (5mm)	Marl		Farnell	884-698
D2	1	LED (red)		Through-hole (5mm)	Marl		Farnell	942-492
D3	1	LED (yellow)		Through-hole (5mm)	Marl		Farnell	942-455
0	1	Push-button Switches		4-leg Through-hole (Push-4)-6mm square	Bourns		Farnell	535-916
1	1	Push-button Switches		4-leg Through-hole (Push-4)-6mm square	Bourns		Farnell	535-916
2	1	Push-button Switches		4-leg Through-hole (Push-4)-6mm square	Bourns		Farnell	535-916
3	1	Push-button Switches		4-leg Through-hole (Push-4)-6mm square	Bourns		Farnell	535-916
4	1	Push-button Switches		4-leg Through-hole (Push-4)-6mm square	Bourns		Farnell	535-916
5	1	Push-button Switches		4-leg Through-hole (Push-4)-6mm square	Bourns		Farnell	535-916
6	1	Push-button Switches		4-leg Through-hole (Push-4)-6mm square	Bourns		Farnell	535-916
7	1	Push-button Switches		4-leg Through-hole (Push-4)-6mm square	Bourns		Farnell	535-916
8	1	Push-button Switches		4-leg Through-hole (Push-4)-6mm square	Bourns		Farnell	535-916
9	1	Push-button Switches		4-leg Through-hole (Push-4)-6mm square	Bourns		Farnell	535-916
*	1	Push-button Switches		4-leg Through-hole (Push-4)-6mm square	Bourns		Farnell	535-916
#	1	Push-button Switches		4-leg Through-hole (Push-4)-6mm square	Bourns		Farnell	535-916
BZ1	1	DC-Buzzer		Through-hole (85db, 1.5V-27V DC)	Stuff	S.E. - B-20-B		
	1	3V Battery	CR2032	Coin type	MAXEL	MAXELCR2032		
BT1	1	Battery Socket		BATT-C	MAXEL	MAXELCR2032		
R11, R2, R3, R4, R5, R6, R9	7	Resistor - 10K			805 Local			
R1, R13, R14	3	Resistor - 330			805 Local			
R10, R12, R7, R8	4	Resistor-10M			805 Local			
C1, C10, C2, C3, C4, C7, C8, C9	8	Capacitor-0.1µF			805 Local			
C6	1	Capacitor-1µF/10V		CAP	Local			
C5	1	Capacitor-2.2 µF/10V		CAP	Local			
J1	1	Power Jack (for adaptor)		power jack for adaptor	Local			
JP1, JP2, JP3, JP4	4	Jumper		SIP-2 (berg strip)	Local			
C11	1	Capacitor-10nF			805 Local			