

rfmd.com

### **RF7115** QUAD-BAND GSM850/GSM900/DCS/PCS TRANSMIT MODULE

#### RoHS Compliant & Pb-Free Product Package Style: Module (7mmx8mm)




### **Features**

- Reduced Solution Size Integrating Antenna Switch and Harmonic Filtering to Decrease Time to Market
- Package 7x8x1.2mm
- IEC 61000-4-2 Compliant
- In/Output Matched to  $50\Omega$
- DC Block on Antenna Port
- GSM850/900 P<sub>OUT</sub>=33.5dBm
- DCS/PCS P<sub>OUT</sub>=30.5dBm
- New Current Limiter

### **Applications**

- GSM850/EGSM900/DCS/PCS Products
- GPRS Class 12 Capable
- Power Star© Module
- 3V Quad-Band Handsets
- Portable Battery-Powered Equipment



Functional Block Diagram

### **Product Description**

The RF7115 is a high-power, high-efficiency transmit module containing RFMD's Power Star<sup>©</sup> integrated power control, integrated pHEMT front end antenna switch and harmonic filtering functionality. All of which combine to provide for best in class harmonic emission control and RX and TX insertion loss. The device is self-contained with  $50\Omega$  input and output terminals with no matching components required. The integrated power control function based on RFMD's patented Power Star<sup>©</sup> control is incorporated, eliminating the need for directional couplers, detector diodes, power control ASIC's, and other power control circuitry; this allows the module to be driven directly from the DAC output. The device is designed for use as the final portion of the transmit chain in GSM850, EGSM900, DCS and PCS GMSK and eliminates the need for PA to antenna switch module matching. On-board power control provides over 70dB control range. The integrated antenna switch allows true quad band TX and RX functionality. Built-in current limiter option may be utilized to minimize power variation in mismatch condition.

0	ptimum Technolog	gy Matching® App	lied
GaAs HBT	SiGe BiCMOS	GaAs pHEMT	GaN HEMT
□ GaAs MESFET □ InGaP HBT	☐ Si BiCMOS ☐ SiGe HBT	Si CMOS	□ RF MEMS
LI INGAP HEI			

nd

RF MIGRO DEVICES®, RFMD®, optimum Technology Matching®, Enabling Wireless Connectivity<sup>10</sup>, PoweStarte, PoweStarte, Poularis<sup>10</sup> and UltimateBlue<sup>10</sup> are trademarks of RFMD. LLC. BLUETOOTH is a trade mark owned in Builenoth SiG. US. LLS A and liberged for use for BFMD. All other code names: a frademarks and residered interameters. are the respective oncourse. Sc2006, EPK Micro Devices Lice.

+1) 326-678-5570 or sales-support

7628 Thorndike Road, Greensboro, NC 27409-9421 · For sales or technical

support, contact R



#### **Absolute Maximum Ratings**

0		
Parameter	Rating	Unit
Supply Voltage	-0.3 to +6.0	V
Power Control Voltage (V <sub>RAMP</sub> )	-0.3 to +1.8	V
Input RF Power	+10	dBm
Max Duty Cycle	50	%
Output Load VSWR	20:1	
Operating Case Temperature	-20 to +85	°C
Storage Temperature	-55 to +150	°C



Exceeding any one or a combination of the Absolute Maximum Rating conditions may cause permanent damage to the device. Extended application of Absolute Maximum Rating conditions to the device may reduce device reliability. Specified typical performance or functional operation of the device under Absolute Maximum Rating conditions is not implied.

RoHS status based on EUDirective2002/95/EC (at time of this document revision).

The information in this publication is believed to be accurate and reliable. However, no responsibility is assumed by RF Micro Devices, Inc. ("RFMD") for its use, nor for any infringement of patents, or other rights of third parties, resulting from its use. No license is granted by implication or otherwise under any patent or patent rights of RFMD. RFMD reserves the right to change component circuitry, recommended application circuitry and specifications at any time without prior notice.

Paramotor	Parameter Specification	Unit	Condition		
Farameter	Min.	Тур.	Max.	Unit	Condition
Overall Power Control V <sub>RAMP</sub>					
Power Control "ON"			1.5	V	Max. P <sub>OUT</sub> , Voltage supplied to the input
Power Control "OFF"		0.2	0.25	V	Min. P <sub>OUT</sub> , Voltage supplied to the input
V <sub>RAMP</sub> Input Capacitance		15	20	pF	DC to 2MHz
V <sub>RAMP</sub> Input Current			10	μΑ	V <sub>RAMP</sub> =V <sub>RAMP MAX</sub>
Turn On/Off Time			2	us	V <sub>RAMP</sub> =0V to V <sub>RAMP MAX</sub>
Power Control Range		50		dB	V <sub>RAMP</sub> =0.25V to V <sub>RAMP MAX</sub>
V <sub>RAMP</sub> P <sub>OUT</sub> BW	2.0	2.5		MHz	
Overall Power Supply					
Power Supply Voltage		3.5		V	Specifications
	3.0		5.5	V	Nominal operating limits
Power Supply Current		1	20	μA	P <sub>IN</sub> <-30dBm, TX Enable=Low, V <sub>RAMP</sub> =0V, Temp=-20°C to +85°C, V <sub>BATT</sub> =5.5V
<b>Overall Control Signals</b>					
B1, B2, B3 "Low"	0	0	0.5	V	
B1, B2, B3 "High"	1.25	2.0	3.0	V	
B1, B2, B3 "High Current"		1	2	uA	
TX Enable "Low"	0	0	0.5		
TX Enable "High"	1.25	2.0	3.0	V	
TX Enable "High Current"		1	2	uA	

rfmd.com

RFMD 💷




Parameter	Specification			1114	
	Min.	Тур.	Max.	Unit	Condition
					Temp=+25°C, V <sub>BATT</sub> =3.5V,
GSM850 Mode					V <sub>RAMP MAX</sub> , P <sub>IN</sub> =4dBm,
					25% Duty Cycle, Pulse Width = $1154  \mu s$
Operating Frequency Range	824		849	MHz	
Maximum Output Power	33.0	34.0		dBm	25% duty cycle, pulse width 1154 us
	32.8			dBm	50% duty cycle, pulse width 2308 us
	31.0			dBm	Temp=+85°C, V <sub>BATT</sub> =3.0V,
					V <sub>RAMP</sub> =V <sub>RAMP MAX</sub> @ V <sub>BATT</sub> =3.0V
Total Efficiency	37	42		%	At P <sub>OUT MAX</sub> , V <sub>BATT</sub> =3.5V
Input Power Range	2	4	6	dBm	Full output power guaranteed at minimum drive level
Output Noise Power		-88	-83	dBm	869MHz to 894MHz, RBW=100kHz, P <sub>OUT</sub> ≥+5dBm
		<-100	-87	dBm	1930MHz to 1990MHz, RBW=100kHz, P <sub>OUT</sub> ≥+5dBm
Forward Isolation 1		-50	-41	dBm	TXEnable=Low, P <sub>IN</sub> =+6dBm, V <sub>RAMP</sub> =0.25V, B1=B2=Low, B3=High
Forward Isolation 2		-29	-15	dBm	TXEnable=High, P <sub>IN</sub> =+6dBm, V <sub>RAMP</sub> =0.25V, B1=B2=Low, B3=High
All Harmonics up to 12.75GHz		-40	-35	dBm	Over all power levels (5dBm to 33dBm)
All Non-Harmonic Spurious			-36	dBm	Over all power levels (5dBm to 33dBm)
Input VSWR			2.5:1		Over all power levels (5dBm to 33dBm)
Output Load VSWR Stability	10:1				Spurious<-36dBm, set $V_{RAMP}$ where $P_{OUT} \leq 33.0$ dBm into 50 $\Omega$ load
Output Load VSWR Ruggedness	20:1				Set $V_{RAMP}$ where $P_{OUT} \le 33.0 \text{ dBm}$ into $50 \Omega$ load. No damage or permanent degradation to part.
Input and Output Impedance		50		Ω	
Note: V <sub>RAMP MAX</sub> =3/8*V <sub>BATT</sub> +0.15	≤1.5V				

RFMD	•))))
rfmd.com	

Parameter	Specification			Unit	
	Min.	Тур.	Max.	Unit	Condition
					Temp=+25°C, V <sub>BATT</sub> =3.5V,
GSM900 Mode					V <sub>RAMP MAX</sub> , P <sub>IN</sub> =4dBm,
					25% Duty Cycle, Pulse Width=1154 $\mu$ s
Operating Frequency Range	880		915	MHz	
Maximum Output Power	33.0	33.5		dBm	25% duty cycle, pulse width 1154 us
	32.8			dBm	50% duty cycle, pulse width 2308us
	31.0			dBm	Temp=+85°C, V <sub>BATT</sub> =3.0V,
					V <sub>RAMP</sub> =V <sub>RAMP MAX</sub>
Total Efficiency	35	40		%	At P <sub>OUT MAX</sub> , V <sub>BATT</sub> =3.5V
Input Power Range	2	4	6	dBm	Full output power guaranteed at minimum drive level
Output Noise Power		-85	-79	dBm	925MHz to 935MHz, RBW=100kHz, P <sub>OUT</sub> ≥+5dBm
		-89	-83	dBm	935MHz to 960MHz, RBW=100kHz, P <sub>OUT</sub> ≥+5dBm
		<-100	-87	dBm	1805MHz to 1880MHz, RBW=100kHz, $P_{OUT} \ge +5$ dBm
Forward Isolation 1		-60	-41	dBm	TXEnable=Low, P <sub>IN</sub> =+6dBm, V <sub>RAMP</sub> =0.25V, B1=High, B2=Low, B3=High
Forward Isolation 2		-27	-15	dBm	TXEnable=High, P <sub>IN</sub> =+6dBm, V <sub>RAMP</sub> =0.25V, B1=High, B2=Low, B3=High
All Harmonics up to 12.75GHz		-40	-35	dBm	Over all power levels (5dBm to 33dBm)
All Non-Harmonic Spurious			-36	dBm	Over all power levels (5dBm to 33dBm)
Input VSWR			2.5:1		Over all power levels (5dBm to 33dBm)
Output Load VSWR Stability	10:1				Spurious<-36dBm, set $V_{RAMP}$ where $P_{OUT} \leq 33.0$ dBm into $50\Omega$ load
Output Load VSWR Ruggedness	20:1				Set $V_{RAMP}$ where $P_{OUT} \leq 33.0 dBm$ into $50 \Omega$ load
Input and Output Impedance		50		Ω	
Note: V <sub>RAMP MAX</sub> =3/8*V <sub>BATT</sub> +0.15	≤1.5V				

rfmd.com

RFMD 💷



Deveneetev		Specification	า	Unit	Condition
Parameter	Min.	Тур.	Max.	Unit	Condition
DCS1800 Mode					Temp=+25°C, V <sub>BATT</sub> =3.5V, V <sub>RAMP MAX</sub> , P <sub>IN</sub> =4dBm, 25% Duty Cycle, Pulse Width=1154µs
Operating Frequency Range	1710		1785	MHz	
Maximum Output Power	30.0	31.0		dBm	25% duty cycle, pulse width 1154 us
	29.8			dBm	50% duty cycle, pulse width 2308 us
	28.0			dBm	Temp=+85°C, V <sub>BATT</sub> =3.0V, V <sub>RAMP</sub> =V <sub>RAMP MAX</sub>
Total Efficiency	32	37		%	At P <sub>OUT MAX</sub> , V <sub>BATT</sub> =3.5V
Input Power Range	2	4	6	dBm	Full output power guaranteed at minimum drive level
Output Noise Power		-92	-87	dBm	1805MHz to 1880MHz, RBW=100kHz, P <sub>OUT</sub> ≥0dBm
		<-100	-87	dBm	925MHz to 935MHz, RBW=100kHz, P <sub>OUT</sub> ≥0dBm
		<-100	-84	dBm	935 MHz to 960 MHz, RBW = 100 kHz, $P_{OUT} \ge 0 dBm$
Forward Isolation 1		-60	-53	dBm	TXEnable=Low, P <sub>IN</sub> =+6dBm, V <sub>RAMP</sub> =0.25V, B1=Low, B2=High, B3=High
Forward Isolation 2		-20	-15	dBm	TXEnable=High, P <sub>IN</sub> =+6dBm, V <sub>RAMP</sub> =0.25V, B1=Low, B2=High, B3=High
All Harmonics up to 12.75GHz		-40	-35	dBm	Over all power levels (0dBm to 30dBm)
All Non-Harmonic Spurious			-36	dBm	Over all power levels (0dBm to 30dBm)
Input VSWR			2.5:1		Over all power levels (0dBm to 30dBm)
Output Load VSWR Stability	10:1				Spurious<-36dBm, set $V_{RAMP}$ where $P_{OUT} \leq$ 30.0dBm into 50 $\Omega$ load
Output Load VSWR Ruggedness	20:1				Set $V_{RAMP}$ where $P_{OUT} \leq 30.0 dBm$ into $50 \Omega$ load. No damage or permanent degradation to part.
Input and Output Impedance		50		Ω	
Note: V <sub>RAMP MAX</sub> =3/8*V <sub>BATT</sub> +0.15	<u>&lt;</u> 1.5V				

RFMD	•))))
rfmd.com	

Parameter	Specification			Unit	Condition
	Min.	Тур.	Max.	Unit	Condition
PCS1900 Mode					Temp=+25°C, V <sub>BATT</sub> =3.5V, V <sub>RAMP MAX</sub> , P <sub>IN</sub> =4dBm, 25% Duty Cycle, Pulse Width=1154µs
Operating Frequency Range	1850		1910	MHz	
Maximum Output Power	30.0	31.0		dBm	25% duty cycle, pulse width 1154 us
	29.8			dBm	50% duty cycle, pulse width 2308 us
	28.0			dBm	Temp=+85°C, V <sub>BATT</sub> =3.0V, V <sub>RAMP</sub> =V <sub>RAMP MAX</sub>
Total Efficiency	32	37		%	At P <sub>OUT MAX</sub> , V <sub>BATT</sub> =3.5V
Input Power Range	2	4	6	dBm	Full output power guaranteed at minimum drive level
Output Noise Power		-92	-87	dBm	1930MHz to 1990MHz, RBW=100kHz, P <sub>OUT</sub> ≥0dBm
		<-100	-87	dBm	869MHz to 894MHz, RBW=100kHz, P <sub>OUT</sub> ≥0dBm
Forward Isolation 1		-60	-53	dBm	TXEnable=Low, P <sub>IN</sub> =+6dBm, V <sub>RAMP</sub> =0.25V, B1=B2=B3=High
Forward Isolation 2		-20	-15	dBm	TXEnable=High, P <sub>IN</sub> =+6dBm, V <sub>RAMP</sub> =0.25V, B1=B2=B3=High
All Harmonics up to 12.75GHz		-40	-35	dBm	Over all power levels (0dBm to 30dBm)
All Non-Harmonic Spurious			-36	dBm	Over all power levels (0dBm to 30dBm)
Input VSWR			2.5:1		Over all power levels (0dBm to 30dBm)
Output Load VSWR Stability	10:1				Spurious<-36dBm, set $V_{RAMP}$ where $P_{OUT} \leq 30.0$ dBm into 50 $\Omega$ load
Output Load VSWR Ruggedness	20:1				Set $V_{RAMP}$ where $P_{OUT} \le 30.0 \text{ dBm}$ into $50 \Omega$ load. No damage or permanent degradation to part.
Input and Output Impedance		50		Ω	
Note: V <sub>RAMP MAX</sub> =3/8*V <sub>BATT</sub> +0.15	<u>&lt;</u> 1.5V				

RFMD .....



Devementer	Parameter Specification Unit	Unit	Condition		
Parameter	Min.	Тур.	Max.	Unit	Condition
RX-Section					Nominal conditions
Insertion Loss, ANT-RX1-4					Temp=+25°C, V <sub>CC</sub> =3.5V
Freq 869MHz to 894MHz		1.0	1.3	dB	TX=Low, B1=Low, B2=Low, B3=High
Freq 925MHz to 960MHz		1.0	1.3	dB	TX=Low, B1=High, B2=Low, B3=X
Freq 1805 MHz to 1880 MHz		1.3	1.6	dB	TX=Low, B1=Low, B2=High, B3=X
Freq 1930MHz to 1990MHz		1.3	1.6	dB	TX=Low, B1=High, B2=High, B3=X
Insertion Loss, ANT-RX1-4					Extreme conditions
Freq 869MHz to 894MHz		1.4	1.7	dB	Temp=-20°C, +25°C, and +85°C, V <sub>CC</sub> =3.0V,
					3.5V, and 5.5V
Freq 925 MHz to 960 MHz		1.4	1.7	dB	
Freq 1805MHz to 1880MHz		1.7	2.0	dB	
Freq 1930MHz to 1990MHz		1.7	2.0	dB	
Ripple, ANT-RX1-4					Nominal conditions
Freq 869MHz to 894MHz		0.02	0.20	dB	Temp=+25°C, V <sub>CC</sub> =3.5V
Freq 925 MHz to 960 MHz		0.02	0.20	dB	
Freq 1805MHz to 1880MHz		0.06	0.20	dB	
Freq 1930MHz to 1990MHz		0.06	0.20	dB	
Return Loss, ANT-RX1-2					Nominal conditions
Freq 869MHz to 894MHz		-22	-15	dB	Temp=+25°C, V <sub>CC</sub> =3.5V
Freq 925MHz to 960MHz		-22	-15	dB	
Return Loss, ANT-RX3-4					
Freq 1805 MHz to 1880 MHz		-14	-12	dB	
Freq 1930MHz to 1990MHz	_	-14	-12	dB	

FMD	•)))
rfmd.com	

Baramator		Specification			Condition
Parameter	Min.	Тур.	Max.	Unit	Condition
X-Section					
solation, ANT-RX1-4					
Freq 824MHz to 849MHz					
RX1		-0.75	10	dBm	Temp=+25°C, V <sub>CC</sub> =3.5V, P <sub>OUT</sub> =33dBm
RX2		-0.75	10	dBm	Temp=+25°C, V <sub>CC</sub> =3.5V, P <sub>OUT</sub> =33dBm
RX3		1.75	10	dBm	Temp=+25°C, V <sub>CC</sub> =3.5V, P <sub>OUT</sub> =33dBm
RX4		1.75	10	dBm	Temp=+25°C, V <sub>CC</sub> =3.5V, P <sub>OUT</sub> =33dBm
Freq 880MHz to 915MHz					
RX1		0.25	10	dBm	Temp=+25°C, V <sub>CC</sub> =3.5V, P <sub>OUT</sub> =33dBm
RX2		0.25	10	dBm	Temp=+25°C, V <sub>CC</sub> =3.5V, P <sub>OUT</sub> =33dBm
RX3		2.50	10	dBm	Temp=+25°C, V <sub>CC</sub> =3.5V, P <sub>OUT</sub> =33dBm
RX4		2.50	10	dBm	Temp=+25°C, V <sub>CC</sub> =3.5V, P <sub>OUT</sub> =33dBm
Freq 1710MHz to 1785MHz					
RX1		8.50	10	dBm	Temp=+25°C, V <sub>CC</sub> =3.5V, P <sub>OUT</sub> =30dBm
RX2		5.00	10	dBm	Temp=+25°C, V <sub>CC</sub> =3.5V, P <sub>OUT</sub> =30dBm
RX3		-5.00	10	dBm	Temp=+25°C, V <sub>CC</sub> =3.5V, P <sub>OUT</sub> =30dBm
RX4		5.50	10	dBm	Temp=+25°C, V <sub>CC</sub> =3.5V, P <sub>OUT</sub> =30dBm
Freq 1850MHz to 1910MHz					
RX1		9.25	10	dBm	Temp=+25°C, V <sub>CC</sub> =3.5V, P <sub>OUT</sub> =30dBm
RX2		6.00	10	dBm	Temp=+25°C, V <sub>CC</sub> =3.5V, P <sub>OUT</sub> =30dBm
RX3		-5.50	10	dBm	Temp=+25°C, V <sub>CC</sub> =3.5V, P <sub>OUT</sub> =30dBm
RX4		6.00	10	dBm	Temp=+25°C, V <sub>CC</sub> =3.5V, P <sub>OUT</sub> =30dBm

Note: Isolation specification max limit set to ensure at least 20dB of isolation. Calculation example: P<sub>OUT</sub>@A<sub>NT</sub>-P<sub>OUT</sub>@KXPort, Lo Band Isolation=33-10=23dB, Hi Band Isolation=30-10=20dB. Additional RX3 circuitry ensures specification for Hi Band TX-RX overlapping frequencies. Lo Band RX-RX overlapping frequencies has sufficient margin.






RFMD ໜ

rfmd.com

Pin	Function	Description	Interface Schematic	
1	VSENSE	Can provide two purposes: 1. The current limiter can be set by adding a resistor to determine the set point. When open, the current limiter feature is fully engaged and shorter the current limiter is disabled. 2. A voltage proportional to the PA current can be detected and used as feedback to the baseband. See application note for further details. BE input to the COMPEQ/CEMPOO based. This is a EQQ input		
2	GSM850/ GSM900 IN	RF input to the GSM850/GSM900 band. This is a 50 $\Omega$ input.		
3	B1	Control pin that together with B2 and B3 selects band of operation.		
4	B2	Control pin that together with B1 and B3 selects band of operation.		
5	VBATT	Power supply for the module. This should be connected to the battery ter- minal using as wide a trace as possible.		
6	B3	Control pin that together with B1 and B2 selects band of operation.		
7	TX ENABLE	This signal enables the PA module for operation with a logic high. The switch is put in TX mode determined by B1, B2, and B3.		
8	VRAMP	VRAMP ramping signal from DAC. A simple RC filter may need to be con-		
0		nected between the DAC output and the V <sub>RAMP</sub> input depending on the baseband selected.		
9	DCS/PCS IN	DCS/PCS IN RF input to the DCS/PCS band. This is a 50 $\Omega$ input.		
10	GND			
11	GND			
12	GND			
13	RX 1	RX 1 port of antenna switch. This is a $50\Omega$ output. Note that there will be a DC voltage present equal to V <sub>BATT</sub> -0.5V.	——————————————————————————————————————	
14	RX 2	RX 2 port of antenna switch. This is a 50 $\Omega$ output. Note that there will be a DC voltage present equal to V_{BATT}-0.5 V.	——————————————————————————————————————	
15	RX 3	RX 3 port of antenna switch. This is a $50\Omega$ output. Note that there will be a DC voltage present equal to V <sub>BATT</sub> -0.5V. Additional logic provided to improve isolation at $2f_0$ of GSM band.		

# RFMD www

Pin	Function	Description	Interface Schematic		
16	RX 4	RX 4 port of antenna switch. This is a 50 $\Omega$ output. Note that there will be a DC voltage present equal to V_{BATT}-0.5V.			
17	GND				
18	GND				
19	GND				
20	GND				
21	ANT	Antenna port of antenna switch. This is a $50\Omega$ output. Provides DC blocking as well as ESD protection.			
22	GND				
23	GND				
Pkg Base	GND				





### **Theory of Operation**

#### **Product Description**

The RF7115 is a high-power, high-efficiency, transmit module (TXM) with fully-integrated power control functionality, harmonic filtering, band selectivity, and TX/RX switching. The TXM is self-contained, with 50Ω I/O terminals with four RX ports allowing true quad band operation. The power control function eliminates all power control circuitry, including directional couplers, diode detectors, and power control ASIC's, etc. The power control capability provides 50dB continuous control range, and 70dB total control range, using a DAC-compatible, analog voltage input. The TX Enable feature provides for PA activation (TX mode) or RX mode/Stand-by. Internal switching provides a low-loss, low-distortion path from the Antenna port to the TX path (or RX port), while maintaining proper isolation. Integrated filtering provides ETSI compliant harmonic suppression at the antenna port even under high mismatch conditions, which is important as modern antennas today often present a load that significantly deviates from nominal impedance.

#### Overview

The RF7115 is a true quad-band GSM850, EGSM900, DCS1800, and PCS1900 power amplifier module with fully integrated power control functionality, harmonic filtering, band selectivity and TX/RX switching. This simplifies the phone design by eliminating the need for the complicated control loop design, harmonic filters, TX/RX switch and possible matching components between these. The power control loop can be driven directly from the DAC output in the baseband circuit. The module has 4 Rx ports for GSM850. EGSM900, DCS1800, and PCS1900 bands of operation. For optimum performance, it is best to use Rx1 and Rx2 for low band, and Rx3 and Rx4 for high band operation. Best forward isolation can be achieved in these states during the off mode as well. To control the mode of operation, there are four logic control signals; TX Enable, B1, B2, and B3. Refer to truth table below for mode of operations. If control signals are limited, eliminate the use of the standby mode and B3 may remain in the high state for all modes of operation. By also changing the don't care state (X) of B1 allows minimum control logic switching between on and off states.

#### Module Control and Antenna Switch Logic


TX_EN	B1	B2	B3	TX Module Mode
0	0	0	0	Stand by mode
0	0	0	1	RX 1
0	1	0	Х	RX 2
0	0	1	Х	RX 3
0	1	1	Х	RX 4
1	х	0	1	TX low band (GSM850/EGSM900)
1	х	1	1	TX high band (DCS1800/PCS1900)





#### **Power Control Theory of Operation**

Most power control systems in GSM sense either forward power or collector/drain current. The RF7115 uses RFMD's Power Star<sup>R</sup> collector voltage control instead of a power or current detector. A high-speed control loop is incorporated to regulate the collector voltage of the amplifier while the stages are held at a constant bias. The basic circuit is shown in the following diagram.



By regulating the power, the stages are held in saturation across all power levels. As the required output power is decreased from full power down to -15dBm, the collector voltage is also decreased. This regulation of output power is demonstrated in Equation 1 where the relationship between collector voltage and output power is shown. Although load impedance affects output power, supply fluctuations are the dominate mode of power variations. With the RF7115 regulating, there are several key factors to consider in the implementation of a transmitter solution for a mobile phone. Some of them are:

$$P_{dBm} = 10 \cdot \log \left[ \frac{\left(2 \cdot V_{CC} - V_{SAT}\right)^2}{8 \cdot R_{LOAD} \cdot 10^{-3}} \right]$$

(Eq. 1)


- Effective efficiency (η<sub>EFF</sub>)
- Current draw and system efficiency
- Power variation due to Supply Voltage
- Power variation due to frequency
- Power variation due to temperature
- Input impedance variation
- Noise power
- Loop stability
- Loop bandwidth variations across power levels
- Burst timing and transient spectrum trade offs
- Harmonics
- Post PA loss
- Insertion loss in receive ports
- TX power leakage into the RX ports
- Performance during VSWR
- Time needed to implement the solution
- Needed board area for the solution

Talk time and power management are key concerns in transmitter design since the power amplifier is the leading current consumer in a mobile terminal. Considering only the power amplifier's efficiency does not provide a true picture for the total system efficiency. It is important to consider effective efficiency which is represented by  $\eta_{EFF}$ . ( $\eta_{EFF}$  considers the loss between the PA and antenna and is a more accurate measurement to determine how much current will be drawn in the application).  $\eta_{FFF}$  is defined by the following relationship (Equation 2):

$$\eta_{EFF} = \frac{10^{\frac{P_{PA} + P_{LOSS}}{10}} - 10^{\frac{P_{IN}}{10}}}{V_{BAT} \cdot I_{BAT} \cdot 10}$$

(Eq. 2)





Where  $P_{PA}$  is the output power from the PA,  $P_{LOSS}$  the insertion loss and  $P_{IN}$  the input power to the PA. The RF7115 improves the effective efficiency by minimizing the  $P_{LOSS}$  term in the equation. An ASM may have a typical loss of 1.2 dB in LB and 1.4 dB in high band. To be added to this is trace losses and mismatch losses. A post PA loss of 1.5 dB in LB and 1.8 dB in HB is common. With the integration of a low loss pHEMT switch and matching network in the same module, higher system efficiency can be achieved.

Output power does not vary due to supply voltage under normal operating conditions if  $V_{RAMP}$  is sufficiently lower than  $V_{BATT}$ . By regulating the collector voltage to the PA the voltage sensitivity is essentially eliminated. This covers most cases where the PA will be operated. However, as the battery discharges and approaches its lower power range the maximum output power from the PA will also drop slightly. In this case, it is important to also decrease  $V_{RAMP}$  to prevent the power control from inducing switching transients. These transients occur as a result of the control loop slowing down and not regulating power in accordance with  $V_{RAMP}$ . The relationship for  $V_{RAMPMAX}$  based on  $V_{BATT}$  is expressed in equation 3.

$$V_{RAMPMAX} = \frac{3}{8} \times V_{BATT} + 0.15 \le 1.5V$$
 (Eq. 3)

The components following the power amplifier often have insertion loss variation with respect to frequency. Usually, there is some length of microstrip that follows the power amplifier. There is also a frequency response found in directional couplers due to variation in the coupling factor over frequency, as well as the sensitivity of the detector diode. Since the RF7115 does not use a directional coupler with a diode detector, these variations do not occur. Also the TX/RX switch with low pass filters that usually follows the PA may contribute to frequency variation. The TX/RX switch incorporated in the RF7115 is very broadband and does not contribute to frequency roll off. Traditionally working with PA modules, some matching network is necessary between the PA output and the input of the TX/RX switch in order to get best possible performance. This work no longer has to be carried out, as this matching network is included in the RF7115.

Noise power in PA's where output power is controlled by changing the bias voltage is often a problem when backing off of output power. The reason is that the gain is changed in all stages and according to the noise formula (Equation 4),

$$F_{TOT} = F1 + \frac{F2 - 1}{G1} + \frac{F3 - 1}{G1 \cdot G2}$$
(Eq. 4)

the noise figure depends on noise factor and gain in all stages. Because the bias point of the RF7115 is kept constant the gain in the first stage is always high and the overall noise power is not increased when decreasing output power.

Power control loop stability often presents many challenges to transmitter design. Designing a proper power control loop involves trade-offs affecting stability, transient spectrum and burst timing.

The RF7115 loop bandwidth is determined by internal bandwidth and does not change with respect to power levels. This makes it easier to maintain loop stability with a high bandwidth loop since the bias voltage and collector voltage do not vary. An often overlooked problem in PA control loops is that a delay not only decreases loop stability it also affects the burst timing when, for instance the input power from the VCO decreases (or increases) with respect to temperature or supply voltage. The burst timing then appears to shift to the right especially at low power levels. The RF7115 is insensitive to a change in input power and the burst timing is constant and requires no software compensation. Switching transients occur when the up and down ramp of the burst is not smooth enough or suddenly changes shape. If the control slope of a PA has an inflection point within the output power range or if the slope is simply too steep it is difficult to prevent switching transients. Controlling the output power by changing the collector voltage is as earlier described based on the physical relationship between voltage swing and output power. Furthermore all stages are kept constantly biased so inflexion points are nonexistent.

Harmonics are natural products of high efficiency power amplifier design. An ideal class "E" saturated power amplifier will produce a perfect square wave. Looking at the Fourier transform of a square wave reveals high harmonic content. Although this is common to all power amplifiers, there are other factors that contribute to conducted harmonic content as well. With most power control methods a peak power diode detector is used to rectify and sense forward power. Through the rectification process there is additional squaring of the waveform resulting in higher harmonics. The RF7115 address this by eliminating the need for the detector diode. Therefore the harmonics coming out of the PA should represent the maximum power of the harmonics throughout the transmit chain. This is based upon proper harmonic termination of the transmit port.

7628 Thorndike Road, Greensboro, NC 27409-9421 · For sales or technical

support, contact RFMD a

(+1) 326-678-5570 or sales-support or find c



#### Performance under VSWR

Often overlooked when designing transmitters is the fact that they normally operate under mismatch conditions while they are designed to operate only under perfect 50 ohm loads. This means that in the real application, performance is degraded. This performance degradation may include reduction in output power, increased harmonic levels, increased transient spectrum and catastrophic failures, breakdown. Traditionally designers have verified that the PA does not break during mismatch and this is all verification that has been carried out during mismatch. Modern antennas in handsets often present a load that significantly deviates from nominal impedance. A VSWR of 5:1 in not uncommon. In order not to disturb other phones in the same and close by cells, it is important that the ETSI specifications for transient spectrum, bust timing and spurious emission are fulfilled even during mismatch conditions. The RF7115 is designed to maintain its performance even under high antenna mismatch conditions.

If power variation into a mismatch condition presents a problem, a current limiting option maybe utilized. The current limiter can be set by adding a resistor to determine the set point. When open, the current limiter feature is fully engaged and shorter the current limiter is disabled. Please refer to application note for further details.

Unlike a current controlled power control loop, the voltage controlled loop is almost impossible to force out of lock. For the current controlled loop this easily happens as the current to the power amplifier that the controller tries to keep constant can not be maintained during some phase angles. If the output stage of the power amplifier faces a high impedance due to mismatch at the antenna, then the last stage simply cannot sink the current it does in a  $50\Omega$  load condition. As the loop detects the lower current, the control voltage to the power amplifier increases in an attempt to keep the current constant. As it is impossible to reach the desired current, the control voltage for the power amplifier rails and the error is accumulated in the integrator in the control loop. When the reference value is lowered when the down ramp starts, the integrator still contains the accumulated error and the control voltage to the power amplifier does not track the reference signal. This means that the burst will be too long and that when the error finally reaches zero in the integrator, the control voltage to the power amplifier suddenly decreases and this will contribute to increased levels of transient spectrum at the down ramp.


The Power Star methodology is superior to the traditional current control method; it allows the transient spectrum in normal operation to be in the order of -35dBm to -40dBm but also both transient spectrum and the power versus time performance is unaffected even with severe mismatch. In addition to this, the harmonics of the RF7115 is designed to be within ETSI limits for usage with realistic antennas.

#### TX/RX Switch

The pHEMT switch integrated in the RF7115 allows for a low loss connection between the antenna port and the four RX ports. The insertion loss in the TX and RX paths is lower than the loss for a traditional pin-diode switch solution, which means lower current consumption in TX mode and better receiver sensitivity.








\*Package thickness is measured from bottom metal surface to topside of package and does not include bottomside soldermask.

Package Style: Module (7mmx8mm)




Pin Out






### **Application Schematic**







### **Evaluation Board Schematic**








### Evaluation Board Layout Board Size 2.0" x 2.0"


Board Thickness 0.052", Board Material FR-4, Multi-layer

Тор










Back



7628 Thorndike Road, Greensboro, NC 27409-9421 · For sales or technical support, contact REND et (+1) 336-678-5570 or sales-support@rfmd.con



### **PCB** Design Requirements


#### **PCB Surface Finish**


The PCB surface finish used for RFMD's qualification process is electroless nickel, immersion gold. Typical thickness is 3µinch to 8µinch gold over 180µinch nickel.

#### **PCB Land Pattern Recommendation**

PCB land patterns for RFMD components are based on IPC-7351 standards and RFMD empirical data. The pad pattern shown has been developed and tested for optimized assembly at RFMD. The PCB land pattern has been developed to accommodate lead and package tolerances. Since surface mount processes vary from company to company, careful process development is recommended.

#### PCB Metal Land and Solder Mask Pattern









### **RoHS\* Banned Material Content**

Yes
0.165
N/A
А
e4

Bill of Materials	Parts Per Million (PPM)					
DIII UI WIALEHAIS	Pb	Cd	Hg	Cr VI	PBB	PBDE
Laminate	0	0	0	0	0	0
Passive Components	30	0	0	0	0	0
Die	0	0	0	0	0	0
Molding Compound	0	0	0	0	0	0
Die Attach Epoxy	0	0	0	0	0	0
Wire	0	0	0	0	0	0
Solder Plating	0	0	0	0	0	0

This RoHS banned material content declaration was prepared solely on information, including analytical data, provided to RFMD by its suppliers, and applies to the Bill of Materials (BOM) revision noted above.

\* DIRECTIVE 2002/95/EC OF THE EUROPEAN PARLIAMENT AND OF THE COUNCIL of 27 January 2003 on the restriction of the use of certain hazardous substances in electrical and electronic equipment

Pb noted in this material declaration is used in glass or ceramics in electronic components which is an allowed exemption from the RoHS regulations, see Annex to Directive 2002/95/EC and amendment 2005/747/EC.

### **Ordering Information**

RF7115SB Power Amp Module 5-Piece Sample Pack blaPower Amp Module 5-Piece Sample Pack bla Module 5-Piece Sample Pack bla

RF7115PCBA-41X Fully Assembled Evaluation Board

