

www.ti.com SLLS970 – NOVEMBER 2009

3.3-V Differential PECL/LVDS to TTL Translator

Check for Samples: SN65EPT21

FEATURES

- 1 ns Propagation Delay
- F_{max} > 300MHz
- Operating Range: V_{CC} = 3.0 V to 3.6 V with GND = 0 V
- 24-mA TTL Output
- Built-In Temperature Compensation
- Drop-In Compatible to the MC10EPT21, MC100EPT21

APPLICATIONS

- Data and Clock Transmission Over Backplane
- Signaling Level Conversion for Clock or Data

DESCRIPTION

The SN65EPT21 is a differential PECL-to-TTL translator. It operates on +3.3 V supply and ground only. The device includes circuitry to maintain inputs at Vcc/2 when left open.

The V_{BB} pin is a reference voltage output for the device. When the device is used in single-ended mode, the unused input should be tied to V_{BB} . This reference voltage can also be used to bias the input when it is ac coupled. When it is used, place a 0.01µF decoupling capacitor between V_{CC} and V_{BB} . Also limit the sink/source current to < 0.5 mA to V_{BB} . Leave V_{BB} open when it is not used.

The SN65EPT21 is housed in an industry standard SOIC-8 package and is also available in an optional TSSOP-8 package.

PIN ASSIGNMENT(Add pullup on BOTH inputs)

D or DGK PACKAGE (TOP VIEW)




Table 1. Pin Descriptions

PIN	FUNCTION
Q	LVTTL/LVCMOS Output
D, D	Differential LVPECL/LVDS/CML Input
V _{CC}	Positive Supply
V_{BB}	Output Reference Voltage
GND	Ground
NC	No Connect
EP	(DFN8 only) Thermal exposed pad must be connected to a sufficient thermal conduit. Electrically connect to the most negative supply (GND) or leave unconnected, floating open.

ORDERING INFORMATION(1)

PART NUMBER	PART MARKING	PACKAGE	LEAD FINISH
SN65EPT21D/DR	EPT21	SOIC	NiPdAu
SN65EPT21DGK/DGKR	SSSI	MSOP	NiPdAu

(1) Leaded device options are not initially available; contact a sales representative for further details.



Please be aware that an important notice concerning availability, standard warranty, and use in critical applications of Texas Instruments semiconductor products and disclaimers thereto appears at the end of this data sheet.

TEXAS INSTRUMENTS

SLLS970 – NOVEMBER 2009 www.ti.com



This integrated circuit can be damaged by ESD. Texas Instruments recommends that all integrated circuits be handled with appropriate precautions. Failure to observe proper handling and installation procedures can cause damage.

ESD damage can range from subtle performance degradation to complete device failure. Precision integrated circuits may be more susceptible to damage because very small parametric changes could cause the device not to meet its published specifications.

ABSOLUTE MAXIMUM RATINGS(1)

PARAMETER	CONDITIONS	VALUE	UNIT
Absolute PECL mode supply voltage	V _{CC} (GND = 0 V)	3.8	V
Sink/source current, V _{BB}		±0.5	mA
PECL input voltage	$GND = 0 V, V_I \le V_{CC}$	0 to 3.8	V
Operating temperature range		-40 to 85	°C
Storage temperature range		-65 to 150	°C

⁽¹⁾ Stresses beyond those listed under absolute maximum ratings may cause permanent damage to the device. These are stress ratings only and functional operation of the device at these or any conditions beyond those indicated under recommended operating conditions is not implied. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

DISSIPATION RATINGS

PACKAGE	CIRCUIT BOARD MODEL	POWER RATING T _A < 25°C (mW)	THERMAL RESISTANCE, JUNCTION-TO-AMBIENT NO AIRFLOW	DERATING FACTOR $T_A > 25^{\circ}C$ (mW/°C)	POWER RATING T _A = 85°C (mW)
SOIC	Low-K	719	139	7	288
	High-K	840	119	8	336
MSOP	Low-K	469	213	5	188
	High-K	527	189	5	211

THERMAL CHARACTERISTICS

over operating free-air temperature range (unless otherwise noted)

	PARAME	MIN	TYP	MAX	UNIT	
θ_{JB}	Junction-to-board thermal resistance	SOIC		79		°C/W
		MSOP		120		
θ_{JC}	Junction-to-case thermal resistance	SOIC		98		°C/W
		MSOP		74		

KEY ATTRIBUTES

CHARACTERISTICS		VALUE
Internal input pull-down resistor		50 kΩ
Internal input pull-up resistor		50 kΩ
Moisture sensitivity level		Level 1
Flammability rating (oxygen index: 28 to	34)	UL 94 V-0 at 0.125 in
Electrostatic discharge	Human body model	2 kV
	Charged-device model	2 kV
	Machine mode	200 V
Meets or exceeds JEDEC Spec EIA/JE	SD78 latchup test	

SLLS970 - NOVEMBER 2009 www.ti.com

PECL DC CHARACTERISTICS

At $V_{CC} = 3.3 \text{ V}$, GND = 0.0 V (unless otherwise noted)⁽¹⁾ (2)

	PARAMETER	TEST CONDITIONS	T _A	= -40°C	;	T,	_A = 25°	С	T _A = 85°C			UNIT
	PARAMETER	TEST CONDITIONS	MIN	TYP	MAX	MIN	TYP	MAX	MIN	TYP	MAX	UNII
V_{IH}	High-level input voltage, single-ended		2075		2420	2075		2420	2075		2420	mV
V _{IL}	Low-level input voltage, single-ended		1355		1675	1355		1675	1355		1675	mV
V_{BB}	Output reference voltage		1910	2009	2160	1910	2034	2160	1910	2026	2160	mV
V _{IHCM} R	High-level input voltage, common-mode range, differential	See (3)	1.2		3.3	1.2		3.3	1.2		3.3	V
I _{IH}	High-level input current				150			150			150	μA
I _{IL}	Low-level input current		-150			-150			-150			μA

The device will meet the specifications after thermal balance has been established when mounted in a socket or printed circuit board with maintained transverse airflow greater than 500 lfpm. Electrical parameters are assured only over the declared operating temperature range. Functional operation of the device exceeding these conditions is not implied. Device specification limit values are applied individually under normal operating conditions and not valid simultaneously.

TTL DC CHARACTERISTICS

At $V_{CC} = 3.3 \text{ V}$, GND = 0.0, $T_A = -40^{\circ}\text{C}$ to 85°C (unless otherwise noted)⁽¹⁾

	PARAMETER	TEST CONDITIONS	MIN	TYP	MAX	UNIT
I _{CCH}	Power supply current	Output is HIGH	5	9	20	mA
I_{CCL}	Power supply current	Output is LOW	8	7.5	26	mA
V _{OH}	High-level output voltage	$I_{OH} = -3.0 \text{ mA}$	2.4	3.05		V
V _{OL}	Low-level output voltage	IOL = 24 mA		0.32	0.5	V
Ios	Output short circuit current		-180	-100	-80	mA

The device will meet the specifications after thermal balance has been established when mounted in a socket or printed circuit board with maintained transverse airflow greater than 500 lfpm. Electrical parameters are assured only over the declared operating temperature range. Functional operation of the device exceeding these conditions is not implied. Device specification limit values are applied individually under normal operating conditions and not valid simultaneously.

AC CHARACTERISTICS

At $V_{CC} = 3.0 \text{ V}$ to 3.6 V, GND = 0.0 V (unless otherwise noted)⁽¹⁾ (2)

	PARAMETER	TEST CONDITIONS	TA	_ = -40°	С	TA	= 25°C	;	T _A = 85°C			UNIT
	PARAMETER	TEST CONDITIONS	MIN	TYP	MAX	MIN	TYP	MAX	MIN	TYP	MAX	UNIT
f _{MAX}	Maximum switching frequency (Figure 1–Figure 3)		300			300			300			MHz
t _{PLH}	Propagation delay	At 1.5 V	1000	1394	1800	1000	1444	1800	1000	1481	1800	ps
t _{PHL}	Propagation delay	At 1.5 V	1000	1140	1900	1000	1280	1900	1000	1421	1900	ps
t _{JITTER}	Random clock jitter (RMS)			2.25	5		3.2	5		3.4	5	ps
t _{SKEW}	Duty Cycle Skew ⁽³⁾			94	250		78	250		62	250	ps
t _{SKPP}	Part-to-Part Skew (3)				500			500			500	ps
V _{PP}	Input swing	See (4)	150		1200	150		1200	150		1200	mV
t _r /t _f	Output rise/fall times	Q, Q (0.8V - 2.0V))	250	500	900	250	500	900	250	500	900	ps

⁽¹⁾ The device will meet the specifications after thermal equilibrium has been established when mounted in a test socket or printed circuit board with maintained transverse airflow greater than 500 lfpm. Electrical parameters are assured only over the declared operating temperature range. Functional operation of the device exceeding these conditions is not implied. Device specification limit values are applied individually under normal operating conditions and not valid simultaneously.

Input parameters vary 1:1 with V_{CC} . $V_{IHCMR(min)}$ varies 1:1 with GND, $V_{IHCMR(max)}$ varies 1:1 with V_{CC} . V_{IHCMR} range is referenced to the most positive side of the differential

 R_L = 500 Ω to GND and C_L = 20 pF to GND. See Figure 4. Measured with 750mV, 50% duty cycle clock source

Skews are measured between outputs under identical transitions

V_{PP(min)} is minimum input swing for which ac parameters are assured.




Figure 1. Maximum Switching Frequency V_{CC}= 3.0 V




Figure 2. Maximum Switching Frequency V_{CC}= 3.3 V

www.ti.com




Figure 3. Maximum Switching Frequency V_{CC} = 3.6 V




Figure 4. TTL Output AC Test Loading Condition




Figure 5. Output Propagation Delay




Figure 6. Output Rise and Fall Times



PACKAGE OPTION ADDENDUM

www.ti.com 16-Apr-2010

PACKAGING INFORMATION

Orderable Device	Status ⁽¹⁾	Package Type	Package Drawing	Pins	Package Qty	Eco Plan ⁽²⁾	Lead/Ball Finish	MSL Peak Temp ⁽³⁾
SN65EPT21D	ACTIVE	SOIC	D	8	75	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
SN65EPT21DGK	ACTIVE	MSOP	DGK	8	80	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
SN65EPT21DGKR	ACTIVE	MSOP	DGK	8	2500	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM
SN65EPT21DR	ACTIVE	SOIC	D	8	2500	Green (RoHS & no Sb/Br)	CU NIPDAU	Level-1-260C-UNLIM

⁽¹⁾ The marketing status values are defined as follows:

ACTIVE: Product device recommended for new designs.

LIFEBUY: TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.

NRND: Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.

PREVIEW: Device has been announced but is not in production. Samples may or may not be available.

OBSOLETE: TI has discontinued the production of the device.

(2) Eco Plan - The planned eco-friendly classification: Pb-Free (RoHS), Pb-Free (RoHS Exempt), or Green (RoHS & no Sb/Br) - please check http://www.ti.com/productcontent for the latest availability information and additional product content details.

TBD: The Pb-Free/Green conversion plan has not been defined.

Pb-Free (RoHS): TI's terms "Lead-Free" or "Pb-Free" mean semiconductor products that are compatible with the current RoHS requirements for all 6 substances, including the requirement that lead not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, TI Pb-Free products are suitable for use in specified lead-free processes.

Pb-Free (RoHS Exempt): This component has a RoHS exemption for either 1) lead-based flip-chip solder bumps used between the die and package, or 2) lead-based die adhesive used between the die and leadframe. The component is otherwise considered Pb-Free (RoHS compatible) as defined above.

Green (RoHS & no Sb/Br): TI defines "Green" to mean Pb-Free (RoHS compatible), and free of Bromine (Br) and Antimony (Sb) based flame retardants (Br or Sb do not exceed 0.1% by weight in homogeneous material)


(3) MSL, Peak Temp. -- The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.


Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.

In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

www.ti.com 20-Jul-2010

TAPE AND REEL INFORMATION





A0	Dimension designed to accommodate the component width
В0	Dimension designed to accommodate the component length
K0	Dimension designed to accommodate the component thickness
W	Overall width of the carrier tape
P1	Pitch between successive cavity centers

QUADRANT ASSIGNMENTS FOR PIN 1 ORIENTATION IN TAPE



*All dimensions are nominal

Device	Package Type	Package Drawing		SPQ	Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
SN65EPT21DGKR	MSOP	DGK	8	2500	330.0	12.4	5.3	3.4	1.4	8.0	12.0	Q1
SN65EPT21DR	SOIC	D	8	2500	330.0	12.4	6.4	5.2	2.1	8.0	12.0	Q1



www.ti.com 20-Jul-2010




*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)
SN65EPT21DGKR	MSOP	DGK	8	2500	346.0	346.0	29.0
SN65EPT21DR	SOIC	D	8	2500	346.0	346.0	29.0

DGK (S-PDSO-G8)

PLASTIC SMALL-OUTLINE PACKAGE




NOTES:

- A. All linear dimensions are in millimeters.
- B. This drawing is subject to change without notice.
- Body length does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed 0.15 per end.
- Body width does not include interlead flash. Interlead flash shall not exceed 0.50 per side.
- E. Falls within JEDEC MO-187 variation AA, except interlead flash.

D (R-PDSO-G8)

PLASTIC SMALL OUTLINE




NOTES:

- A. All linear dimensions are in inches (millimeters).
- B. This drawing is subject to change without notice.
- Body length does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed 0.006 (0,15) each side.
- Body width does not include interlead flash. Interlead flash shall not exceed 0.017 (0,43) each side.
- E. Reference JEDEC MS-012 variation AA.



D (R-PDSO-G8)

PLASTIC SMALL OUTLINE



NOTES:

- A. All linear dimensions are in millimeters.
- B. This drawing is subject to change without notice.
- C. Publication IPC-7351 is recommended for alternate designs.
- D. Laser cutting apertures with trapezoidal walls and also rounding corners will offer better paste release. Customers should contact their board assembly site for stencil design recommendations. Refer to IPC-7525 for other stencil recommendations.
- E. Customers should contact their board fabrication site for solder mask tolerances between and around signal pads.

IMPORTANT NOTICE

Texas Instruments Incorporated and its subsidiaries (TI) reserve the right to make corrections, modifications, enhancements, improvements, and other changes to its products and services at any time and to discontinue any product or service without notice. Customers should obtain the latest relevant information before placing orders and should verify that such information is current and complete. All products are sold subject to TI's terms and conditions of sale supplied at the time of order acknowledgment.

TI warrants performance of its hardware products to the specifications applicable at the time of sale in accordance with TI's standard warranty. Testing and other quality control techniques are used to the extent TI deems necessary to support this warranty. Except where mandated by government requirements, testing of all parameters of each product is not necessarily performed.

TI assumes no liability for applications assistance or customer product design. Customers are responsible for their products and applications using TI components. To minimize the risks associated with customer products and applications, customers should provide adequate design and operating safeguards.

TI does not warrant or represent that any license, either express or implied, is granted under any TI patent right, copyright, mask work right, or other TI intellectual property right relating to any combination, machine, or process in which TI products or services are used. Information published by TI regarding third-party products or services does not constitute a license from TI to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property of the third party, or a license from TI under the patents or other intellectual property of TI.

Reproduction of TI information in TI data books or data sheets is permissible only if reproduction is without alteration and is accompanied by all associated warranties, conditions, limitations, and notices. Reproduction of this information with alteration is an unfair and deceptive business practice. TI is not responsible or liable for such altered documentation. Information of third parties may be subject to additional restrictions.

Resale of TI products or services with statements different from or beyond the parameters stated by TI for that product or service voids all express and any implied warranties for the associated TI product or service and is an unfair and deceptive business practice. TI is not responsible or liable for any such statements.

TI products are not authorized for use in safety-critical applications (such as life support) where a failure of the TI product would reasonably be expected to cause severe personal injury or death, unless officers of the parties have executed an agreement specifically governing such use. Buyers represent that they have all necessary expertise in the safety and regulatory ramifications of their applications, and acknowledge and agree that they are solely responsible for all legal, regulatory and safety-related requirements concerning their products and any use of TI products in such safety-critical applications, notwithstanding any applications-related information or support that may be provided by TI. Further, Buyers must fully indemnify TI and its representatives against any damages arising out of the use of TI products in such safety-critical applications.

TI products are neither designed nor intended for use in military/aerospace applications or environments unless the TI products are specifically designated by TI as military-grade or "enhanced plastic." Only products designated by TI as military-grade meet military specifications. Buyers acknowledge and agree that any such use of TI products which TI has not designated as military-grade is solely at the Buyer's risk, and that they are solely responsible for compliance with all legal and regulatory requirements in connection with such use.

TI products are neither designed nor intended for use in automotive applications or environments unless the specific TI products are designated by TI as compliant with ISO/TS 16949 requirements. Buyers acknowledge and agree that, if they use any non-designated products in automotive applications, TI will not be responsible for any failure to meet such requirements.

Following are URLs where you can obtain information on other Texas Instruments products and application solutions:

- . .

Products		Applications			
Audio	www.ti.com/audio	Communications and Telecom	www.ti.com/communications		
Amplifiers	amplifier.ti.com	Computers and Peripherals	www.ti.com/computers		
Data Converters	dataconverter.ti.com	Consumer Electronics	www.ti.com/consumer-apps		
DLP® Products	www.dlp.com	Energy and Lighting	www.ti.com/energy		
DSP	dsp.ti.com	Industrial	www.ti.com/industrial		
Clocks and Timers	www.ti.com/clocks	Medical	www.ti.com/medical		
Interface	interface.ti.com	Security	www.ti.com/security		
Logic	logic.ti.com	Space, Avionics and Defense	www.ti.com/space-avionics-defense		
Power Mgmt	power.ti.com	Transportation and Automotive	www.ti.com/automotive		
Microcontrollers	microcontroller.ti.com	Video and Imaging	www.ti.com/video		
RFID	www.ti-rfid.com	Wireless	www.ti.com/wireless-apps		
RF/IF and ZigBee® Solutions	www.ti.com/lprf				
	Audio Amplifiers Data Converters DLP® Products DSP Clocks and Timers Interface Logic Power Mgmt Microcontrollers RFID	Audio www.ti.com/audio Amplifiers amplifier.ti.com Data Converters dataconverter.ti.com DLP® Products www.dlp.com DSP dsp.ti.com Clocks and Timers www.ti.com/clocks Interface interface.ti.com Logic logic.ti.com Power Mgmt power.ti.com Microcontrollers microcontroller.ti.com RFID www.ti.rid.com	Audio www.ti.com/audio Communications and Telecom Amplifiers amplifier.ti.com Computers and Peripherals Data Converters dataconverter.ti.com Consumer Electronics DLP® Products www.dlp.com Energy and Lighting DSP dsp.ti.com Industrial Clocks and Timers www.ti.com/clocks Medical Interface interface.ti.com Security Logic logic.ti.com Space, Avionics and Defense Power Mgmt power.ti.com Transportation and Automotive Microcontrollers microcontroller.ti.com Wireless Wireless		

TI E2E Community Home Page <u>e2e.ti.com</u>

Mailing Address: Texas Instruments, Post Office Box 655303, Dallas, Texas 75265 Copyright © 2011, Texas Instruments Incorporated

